

Charging a Sonesse 30 WF Motor

To charge a Somfy Sonesse WF RTS Li-ion motor, locate the charging port on the motor's head, then connect the charging cable from the Somfy WireFree Li-ion Charger to the motor's port and plug the charger into an electrical outlet. An LED indicator on the charger will turn red while charging and green when fully charged.

Step-by-step charging instructions:

1. **Locate the Charging Port:**

- Find the charging port on the head of the Sonesse motor. If your shading product has a headbox, a short cable may already be plugged into the motor and accessible through a cable exit for easier charging.

2. **Connect the Charger:**

- Connect the cable from the Somfy WireFree Li-ion Charger into the charging port on the motor. It is extremely important the charger is put in the correct way, or it will damage the motor charging pins. – The lip of the charger is to be facing towards the outer side of the motor



3. **Plug into Outlet:**

- Plug the charger into a nearby electrical wall socket.

4. **Monitor the LED Indicator:**

- The LED indicator on the charger's wall plug will illuminate:
- **Solid Red:** Indicates the device is charging.
- **Solid Orange:** Indicates charging is near completion.
- **Solid Green:** Indicates the battery is fully charged.

5. **Disconnect the Charger:**

- Once the LED turns green, disconnect the charger from the device and the wall plug.

Important Information:

- Ensure the charger's plug is correctly inserted into the motor the right way around or this can bend the pins inside the motor cavity. – See directions on the charger itself.
- The LED light on the charger indicates the charging status, turning red while charging and green when complete.