

Q-Motion Gen 3

Factory Reset

This will erase all limits and paired remotes

1. Select the channel on the remote the blind is paired to

2. **Press and release the UP button**
(Blind will move to the top limit)

3. Using a paper clip, **press the program button** on the back of the remote control (The channel LED's will scroll back and forth when in programming mode)

4. **Press and hold the DOWN button** until the blind moves downwards (Approx. 8 seconds)

5. Pull the bottom bar more than 250mm
(Blind will jog in response)

6. Blind is now reset.
All limits and pairing with remote control have been reset